

















K21

KEYCOOL

产品信息:

尺寸:	~92x136x41mm	重量:	~220g/450g
系统:	Windows/MaC	配列:	21键
电池:	1500mAh	键帽:	PBT/原厂
供电:	Type-C DC5V-1A	灯光:	RGB
热插拔:	全键热插拔轴座	宏设:	支持

快捷键功能

	关/开背光		调整背光颜色
	恢复出厂设置		计算器 (Game)
	蓝牙设备1		背光亮度-
	蓝牙设备2		背光亮度+
	蓝牙设备3		查询电量
	2.4G模式		背光速度-
	有线模式		背光速度+
	切换背光灯效		切换FN层 (Game)

Fn组合键使用方法: 按住Fn不放再按下对应的按键即可触发组合快捷键

充电方法

使用数据线连接电脑或5V1A及以下功率的充电器即可为键盘充电
特别提醒: 建议仅使用电脑USB接口为键盘充电
请勿使用充电功率高于5V1A的充电器为键盘充电
如因使用大功率充电器造成键盘损坏, 将无法享受质保服务

省电模式

短按Fn+Back进入省电模式

续航时间

开启灯光理论续航时间11h
省电模式理论续航时间95h

指示灯位置

w: 电量和无线状态指示灯
num: 数字锁定指示灯

电量提示:

电量过低时, W红灯快闪
充电时, 绿灯常亮
充电完成, W充电指示灯关闭

关于个性键:

键盘最上面一排从左到右依次为

Esc Tab Fn Back

电量查询:

背光开启时, 按下组合键Fn+, 背光熄灭, FN到, 键亮灯并显示电量占比(如下图)

-	3	6	9	*	FN
10%	20%	30%	40%	80%	100%

2.4G配对

1. 键盘开机后长按Fn+4直至配对指示灯快闪进入2.4G对码模式
2. 插入2.4G接收器, 将键盘尽可能靠近2.4G接收器
3. 对码成功后退出对码, 指示灯常亮2s
4. 若还未成功找到对码设备, 30s后指示灯熄灭并进入休眠, 请重新进行对码操作

有线模式

将数据线插入到电脑端的USB接口上, 同时将Type-c插头插入到本键盘Type-c接口上, 键盘上按住Fn不放再按一下5切换为有线模式

蓝牙配对

1. 键盘开机后, 长按Fn+1/2/3直至指示灯快闪进入配对模式
2. 在蓝牙接收设备上找到K21pro-3.0/5.0并与之配对, 配对完成后指示灯常亮2s
3. 若配对失败, 键盘指示灯熄灭并进入休眠, 请重新配对

键盘开关

当键盘未连接USB时, 拨动开关即可开机并进入无线工作模式, 再次拨动开关即可关机。(有线连接中不会关机)

键盘驱动

驱动下载与安装
下载网址: www.kc-keycool.com
适配系统: Windows
邮箱: support@keycool.vip

下载方式:

1. 打开凯酷官网, 点击驱动, 找到与型号对应的驱动
2. 解压下载好的驱动包, 点击exe文件安装。
3. 安装完成后, 使用有线模式连接电脑, 驱动程序会自动识别键盘。
4. 连接完成, 开始使用驱动。

驱动更新

打开驱动程序, 点击右下角更新驱动, 即可获取最新版本的驱动。

K21

KEYCOOL

PRODUCT INFORMATION:

Measure:	≈92x136x41mm	Weight:	≈220g/450g
System:	Windows/Mac	Assortment:	21 key
Battery:	1500mAh	Keycap:	PBT/Original factory
Supply electricity:	Type-C DC5V-1A	Lamplight:	RGB
Hotswap:	yes	Macro :	support

Shortcut key function

	Turn off/on the backlight		Adjust the backlight color
	Restore factory settings		Calculator _(win)
	Bluetooth device 1		Backlight brightness-
	Bluetooth device 2		Backlight brightness+
	Bluetooth device 3		Inquire about electricity quantity
	2.4g mode		Backlight speed-
	Wired mode		Backlight speed+
	Switching backlight effect		Switching FN layer _(win)

How to use Fn key combination: Press and hold Fn and then press the corresponding key to trigger the combination shortcut key.

Charging method

The keyboard can be charged by connecting a data cable to a computer or a charger with power of 5V1A or less.

Special reminder: It is recommended to use only the USB interface of the computer to charge the keyboard.

Do not use a charger with charging power higher than 5V1A to charge the keyboard. If the keyboard is damaged due to the use of high-power charger, you will not be able to enjoy the warranty service.

Power saving mode

Press Fn+Back briefly to enter power saving mode.

Endurance

Turn on the lights. Theoretical battery life is 11h. Theoretical battery life of power saving mode is 95h.

Indicator position

w: Power and wireless status indicators
num: Digital lock indicator light

Electric quantity prompt:

When the battery is too low, the W red light flashes.
When charging, the green light is always on.
When the charging is completed, the W charging indicator light is turned off.

Electric quantity inquiry:

When the backlight is turned on, press the combination key Fn+. The backlight goes out, and the keys Fn to light up and display the power ratio (as shown below).

-	3	6	9	*	FN
10%	20%	30%	40%	80%	100%

About personality keys:

The top row of the keyboard is from left to right.

Esc	Tab	Fn	Back

2.4G pairing

- After the keyboard is turned on, press fn+4 for a long time until the pairing indicator flashes to enter the 2.4G code matching mode.
- Insert the 2.4G receiver and place the keyboard as close as possible to the 2.4G receiver.
- Exit the code alignment after the code alignment is successful, and the indicator light is always on for 2s.
- If the code matching device has not been found successfully, and the 30s indicator goes out and goes to sleep, please perform code matching operation again.

Wired mode

Insert the data cable into the USB interface of the computer, and at the same time insert the Type-c plug into the Type-c interface of this keyboard. Press and hold Fn on the keyboard and then press 5 to switch the wired mode.

Bluetooth pairing

- After the keyboard is turned on, press and hold Fn+1/2/3 until the indicator light flashes to enter the pairing mode.
- Find K21pro-3.0/5.0 on the Bluetooth receiving device and pair it. After pairing, the indicator light will always be on for 2s.
- If the pairing fails, the keyboard indicator goes out and goes to sleep, please pair again.

Keyboard switch

When the keyboard is not connected to USB, flip the switch to turn it on and enter the wireless working mode, and flip the switch again to turn it off. (It will not be turned off in wired connection)

KEYBOARD DRIVER:

Driver download and installation

Download URL: www.kc-keycool.com
System: Windows
mailbox: support@keycool.vip

Download method:

- Open the KEYCOOL official website, click the driver and find the driver corresponding to the model.
- Unzip the downloaded driver package and click the exe file to install it.
- After the installation, connect the computer in wired mode, and the driver will automatically recognize the keyboard.
- After the connection is completed, start using the driver.

Driver update

Open the driver and click Update Driver in the lower right corner to get the latest version of the driver