

K19

KEYCOOL

产品信息:

尺寸:	≈92x136x41mm	重量:	≈220g
系统:	Windows/MaC	配列:	19键+1旋钮
电池:	1500mAh	键帽:	PBT
供电:	Type-C DC5V-1A	灯光:	RGB
热插拔:	是	宏设:	支持
轮询率:	1000HZ	结构:	Gasket

快捷键功能

Fn + Back	恢复出厂设置 (K19 Pro)	Fn + B	计算器 (QMK)
Fn + 1	蓝牙设备1	Fn + /	背光速度-
Fn + 2	蓝牙设备2	Fn + *	背光速度+
Fn + 3	蓝牙设备3	Fn + [切换旋钮灯效
Fn + 4	2.4G模式	Fn +]	切换旋钮颜色
Fn + 5	有线模式	Fn + Esc	查询电量
Fn + 6	切换背光灯效	Fn + Win	省电模式
Fn + 7	切换背光颜色	Fn + 旋钮	切换旋钮控制模式

Fn组合键使用方法: 按住Fn不放再按下对应的按键即可触发组合快捷键

充电方法

使用数据线连接电脑或5V1A及以下功率的充电器即可为键盘充电
特别提醒: 建议仅使用电脑USB接口为键盘充电
请勿使用充电功率高于5V1A的充电器为键盘充电
如因使用大功率充电器造成键盘损坏, 将无法享受质保服务

指示灯和按键说明

	: 电量指示灯
	: 数字锁定指示灯
	: 连接通道指示灯

旋钮



电量提示:

电量过低时, 电量指示灯红灯快闪
充电时, 电量指示灯常亮
充电完成, 电量指示灯关闭

电量查询:

背光开启时, 按下组合键Fn+ 背光熄灭,
到FN亮灯并显示电量占比(如下图)

-	3	6	9	*	FN
10%	20%	30%	40%	80%	100%

关于旋钮:

切换模式:短按FN+旋钮切换多媒体/背光模式。
多媒体模式:短按ESC, 顺时针旋转调大音量, 逆时针旋转调小音量。
RGB模式:短按ESC, 顺时针旋转调亮背光亮度, 逆时针旋转调暗背光亮度。
注意:旋钮功能可通过自定义软件进行自定义。

2.4G配对

- 1.键盘开机后长按Fn + 4直至配对指示灯快闪进入2.4G对码模式
- 2.插入2.4G接收器, 将键盘尽可能靠近2.4G接收器
- 3.对码成功后退出对码, 指示灯常亮2s
- 4.若还未成功找到对码设备, 30s指示灯熄灭后并进入休眠, 请重新进行对码操作

有线模式

将数据线插入到电脑端的USB接口上, 同时将Type-c插头插入到本键盘Type-c接口上, 键盘上按住Fn不放再按一下5切换为有线模式

蓝牙配对

- 1.键盘开机后, 长按Fn+1/2/3直至指示灯快闪进入配对模式
- 2.在蓝牙接收设备上找到K21pro-3.0/5.0并与之配对, 配对完成后指示灯常亮2s
- 3.若配对失败, 键盘指示灯熄灭并进入休眠, 请重新配对

键盘开关

当键盘未连接USB时, 拨动开关即可开机并进入无线工作模式, 再次拨动开关即可关机。(有线连接中不会关机)

键盘驱动

驱动下载与安装
下载网址: www.kc-keycool.com
适配系统: Windows
邮箱: support@keycool.vip

下载方式:

- 1.打开凯酷官网, 点击驱动,找到与型号对应的驱动
- 2.解压下载好的驱动包, 点击exe文件安装。
- 3.安装完成后, 使用有线模式连接电脑, 驱动程序会自动识别键盘。
- 4.连接完成, 开始使用驱动。

驱动更新

打开驱动程序, 点击右下角更新驱动, 即可获取最新版本的驱动。

















K19

KEYCOOL

PRODUCT INFORMATION:

Measure:	≈92x136x41mm	Weight:	≈220g
System:	Windows/Mac	Assortment:	19key+1knob
Battery:	1500mAh	keycap:	PBT
Supply electricity:	Type-C DC5V-1A	Lamplight:	RGB
Hotswap:	yes	Hongshe:	Support
Polling rate:	1000HZ	Structure:	Gasket

Shortcut key function

 Restore factory settings <small>(Press and hold for 3 seconds)</small>	 calculator <small>(only with)</small>
 Bluetooth device1	 Backlight speed-
 Bluetooth device2	 Backlight speed+
 Bluetooth device3	 Switching knob light effect
 2.4G mode	 Toggle knob color
 Wired mode	 Inquire about electricity quantity
 Switching backlight effect	 Power saving mode
 Switch backlight color	 Switch knob control mode

How to use Fn key combination: Press and hold Fn and then press the corresponding key to trigger the combination shortcut key.



Charging method

The keyboard can be charged by connecting a data cable to a computer or a charger with power of 5V1A or less.

Special reminder: It is recommended to use only the USB interface of the computer to charge the keyboard.

Do not use a charger with charging power higher than 5V1A to charge the keyboard. If the keyboard is damaged due to the use of high-power charger, you will not be able to enjoy the warranty service.

Indicator lights and buttons

	: Power indicator lamp
NUM	: Digital lock indicator light
	: Connecting channel indicator light



Electric quantity prompt:

When the battery is low, the red light of the battery indicator flashes.

When charging, the power indicator is always on. When charging is completed, the power indicator is turned off.

Electric quantity inquiry:

When the backlight is turned on, press the combination key Fn+. The backlight goes out, and the keys FN to light up and display the power ratio (as shown below).

-	3	6	9	*	FN
10%	20%	30%	40%	80%	100%

2.4G pairing

1. After the keyboard is turned on, press fn+4 for a long time until the pairing indicator flashes to enter the 2.4G code matching mode.
2. Insert the 2.4G receiver and place the keyboard as close as possible to the 2.4G receiver.
3. Exit the code alignment after the code alignment is successful, and the indicator light is always on for 2s.
4. If the code matching device has not been found successfully, and the 30s indicator goes out and goes to sleep, please perform code matching operation again.

Wired mode

Insert the data cable into the USB interface of the computer, and at the same time insert the Type-c plug into the Type-c interface of this keyboard. Press and hold Fn on the keyboard and then press 5 to switch the wired mode.

Bluetooth pairing

1. After the keyboard is turned on, press and hold Fn+1/2/3 until the indicator light flashes to enter the pairing mode.
2. Find K21pro-3.0/5.0 on the Bluetooth receiving device and pair it. After pairing, the indicator light will always be on for 2s.
3. If the pairing fails, the keyboard indicator goes out and goes to sleep, please pair again.

About the knob:

Switching mode: Press the FN+ knob briefly to switch the multimedia/backlight mode.

Multimedia mode: press ESC briefly, turn it clockwise to increase the volume, and turn it counterclockwise to decrease the volume.

RGB mode: short press ESC, rotate clockwise to brighten the backlight brightness, and rotate counterclockwise to dim the backlight brightness.

Note: The knob function can be customized by customization software.

Keyboard switch

When the keyboard is not connected to USB, flip the switch to turn it on and enter the wireless working mode, and flip the switch again to turn it off. (It will not be turned off in wired connection)

KEYBOARD DRIVER:

Driver download and installation

Download URL: www.kc-keycool.com

System: Windows

mailbox: support@keycool.vip

Download method:

1. Open the KEYCOOL official website, click the driver and find the driver corresponding to the model.
2. Unzip the downloaded driver package and click the exe file to install it.
3. After the installation, connect the computer in wired mode, and the driver will automatically recognize the keyboard.
4. After the connection is completed, start using the driver.

Driver update

Open the driver and click Update Driver in the lower right corner to get the latest version of the driver